

**POWER SUPPLY UNIT  
TYPE : PS 401H**

Technical Data



**FEATURES :**

- ❑ Output rating 200 watts
- ❑ Generates +/-6V D.C. at 8.5 amps, +/-12V D.C. at 3 amps and +/-24V D.C at 1.5 amp
- ❑ Noise and ripple 10mV for +/-6V and 3mV for +/-12V & +/-24V
- ❑ Regulation better than +/-0.05% for +/-12V & +/-24V and +/-0.1% for +/-6V

**Power Supply PS401H** has been exclusively designed for delivering higher power outputs upto a maximum of 200 Watts. This has additionally +/-6V DC at 8.5A in addition to the other low voltage outputs as given by PS401. It is designed to mate with the Standard Instrumentation Bin IB401. Both rack mounting and table top arrangements are possible. The LV supplies given out by this power supply are highly stable, with good regulation and low ripple.

**SPECIFICATIONS**

**Input Voltage :** 230V ac, single phase 50Hz with 10% variation in input voltage range

**Frequency :** 50Hz + or - 3Hz

**Current :** 1.5A @ 200W output .

**DC output :**

+/-6V DC @ 8.5A

+/-12V DC @ 3A

+/-24V DC @ 1.5A

Total combined load not to exceed 200W

**AC output :**

Voltage : 230V AC

Frequency : 50Hz +/-3Hz

Current : 0.5 amp (max)

**Regulation :**

for +/-12V and 24V +/-0.05% (total band 0.1%), for +/-6V +/-0.1% (total band 0.2%), Over the combined range of zero to full load and specified mains variation, for measurements made within 1 min.period.

**Stability :**

for +/-12V and +/-24V is +/-0.3%, for +/-6V is +/-0.6% over any 24 hrs period at constant ambient temperature. Over the combined range of no load to full load and specified mains variation after 60 min. warmup.

**Temperature Range :**

0 to 50 deg. C ambient.

**Temperature Coefficient :**

0.02% per deg. C over 0 to 50 deg. C ambient.

**Noise & Ripple (rms) :**

For +/-12V & +/-24V 3mV, for +/-6V 10mV

**Recovery Time :**

+/-12V and +/-24V outputs will recover within +/-0.1% and +/-6V outputs will recover within +/-1% of steady state value within 1000 micro seconds following any change in specified line voltage or between 10 to 100% full load.